

Interface for integration of Midea air conditioners into KNX TP-1 (EIB) control systems

Compatible with VRF air conditioners line commercialized by Midea Application's Program Version: 1.0

USER MANUAL

Issue date: 07/2020 r1.4 ENGLISH





Interface for integration of Midea air conditioners into KNX TP-1 (EIB) control systems. Compatible with VRF air conditioners line commercialized by Midea.

Application's Program Version: 1.0

ORDER CODE	LEGACY ORDER CODE
INKNXMID001I000	MD-AC-KNX-1B
INKNXMID016I000	MD-AC-KNX-16
INKNXMID064I000	MD-AC-KNX-64



Important User Information

Disclaimer

The information in this document is for informational purposes only. Please inform HMS Industrial Networks of any inaccuracies or omissions found in this document. HMS Industrial Networks disclaims any responsibility or liability for any errors that may appear in this document.

HMS Industrial Networks reserves the right to modify its products in line with its policy of continuous product development. The information in this document shall therefore not be construed as a commitment on the part of HMS Industrial Networks and is subject to change without notice. HMS Industrial Networks makes no commitment to update or keep current the information in this document.

The data, examples and illustrations found in this document are included for illustrative purposes and are only intended to help improve understanding of the functionality and handling of the product. In view of the wide range of possible applications of the product, and because of the many variables and requirements associated with any particular implementation, HMS Industrial Networks cannot assume responsibility or liability for actual use based on the data, examples or illustrations included in this document nor for any damages incurred during installation of the product. Those responsible for the use of the product must acquire sufficient knowledge in order to ensure that the product is used correctly in their specific application and that the application meets all performance and safety requirements including any applicable laws, regulations, codes and standards. Further, HMS Industrial Networks will under no circumstances assume liability or responsibility for any problems that may arise as a result from the use of undocumented features or functional side effects found outside the documented scope of the product. The effects caused by any direct or indirect use of such aspects of the product are undefined and may include e.g. compatibility issues and stability issues.



INDEX

1 Presentation
2 Connection
3 Configuration and setup
4 ETS Parameters
4.1 General configuration
4.1.1 Download latest database entry for this product and its User Manual from: 9
4.1.2 Intesis Product
4.1.3 Number of Indoor Units in ETS
4.1.4 First Status Updated to KNX 10
4.1.5 Enable object "Error Code [2byte]" 10
4.1.6 Enable object "Error Text Code [14byte]"10
4.2 AC supported features 11
4.2.1 Supported operating modes 11
4.2.2 Supported fan speeds 12
4.3 Global mode configuration 12
4.3.1 Enable use of "Operating Mode" objects
4.3.2 Enable use of Mode Heat / Cool bit obj
4.3.3 Enable use of + / - object for Mode
4.3.4 Enable use of bit-type Mode objects (for control)
4.3.5 Enable use of bit-type Mode objects (for status)
4.3.6 Enable use of Text object for Mode 14
4.4 Fan Speed Configuration dialog 15
4.4.1 DPT object type for fan speed 15
4.4.2 Enable use of +/- object for Fan Speed 17
4.4.3 Enable use of bit-type Fan Speed objects (for Control)
4.4.4 Enable use of bit-type Fan Speed objects (for Status)
4.4.5 Enable use of Text object for Fan Speed
4.5 Global Vanes U-D configuration
4.5.1 Enable use of Text object for Vanes U-D
4.6 Global temperature configuration
4.6.1 Enable use of +/- obj for Setpoint
4.6.2 Ambient Ref. Temp. is provided from KNX
4.7 Remote Lock Configuration 22
4.7.1 Enable Remote Lock Objects
4.7.2 Initial state of remote lock
4.8 Addressing of Indoor Units
4.9 License
5 Specifications
6 AC Unit Types compatibility
7 Error Codes
Appendix A – Communication Objects Table



1 Presentation



INKNXMID---I000 allows a complete and natural integration of Midea air conditioners with KNX control systems.

Compatible with all models of VRF line of Midea air conditioners.

Main features:

- Reduced dimensions. Installation even inside the A.C. indoor unit.
- Quick and non visible installation.
- External power not required.
- Direct connection to the KNX EIB bus.
- Direct connection to the AC indoor unit.
- Fully KNX interoperable, configuration from ETS.
- Multiple objects for control (of different types: bit, byte, characters...).
- Control of the AC unit based in the ambient temperature read by the own AC unit, or in the ambient temperature read by any KNX thermostat.
- Total Control and Monitoring of the AC unit from KNX, including monitoring of AC unit's state of internal variables and error indication and error code.
- AC unit can be controlled simultaneously by the IR remote control of the AC unit and by KNX.



K3 Ø Ø Ø

<u>ю</u>

2 Connection

Connection of the interface to the AC indoor unit:

Disconnect mains power from the AC unit. Open the front cover of the indoor unit in order to have access to the internal control board. In the control board locate the socket connector marked as XYE.

Using a 3 wires cable, connect the EXY connector from the INKNXMID---I000 to the XYE connector of the AC unit's control board.

Fix the INKNXMID---I000 inside or outside the AC indoor unit depending on your needs – remember that INKNXMID---I000 must be also connected to the KNX bus. Close the AC indoor unit's front cover again.

IMPORTANT: If the INKNXMID---I000 gateway is **not** placed at one end of the EXY bus, the terminal resistor should be deactivated. Remove Jumper 1 to deactivate the 120 Ω terminal resistor.

Connection of the interface to the KNX bus:

Disconnect power of the KNX bus. Connect the interface to the KNX TP-1 (EIB) bus using the KNX standard connector (red/grey) of the interface, respect polarity. Reconnect power of the KNX bus.

Connections diagram:



Figure 2.1 Default parameter configuration

△ Please note that address of indoor unit must be set accordingly to the System in parametres dialog. See *4.1.3 Number of Indoor Units in ETS* for more information.



3 Configuration and setup

This is a fully compatible KNX device which must be configured and setup using standard KNX tool ETS.

ETS project for this device can be downloaded from: https://intesis.com/products/ac-interfaces/midea-gateways/midea-knx-vrf-md-ac-knx

Please consult the README.txt file, located inside the downloaded zip file, to find instructions on how to install the database.



4 ETS Parameters

When imported to the ETS software for the first time, the gateway shows the following default parameter configuration:

Device: 1.1.1 MD-AC-KNX		
General configuration	Devenland latest database entry for this	http://www.interin.com
AC supported features	product and its User Manual from:	http://www.intesis.com
Global Mode configuration		
Global Fan Speed configuration	Intesis Product	MD-AC-KNX-1B
Global Vanes U-D configuration		
Global Temperature configuration	Number of Indoor Units in ETS	
Remote Lock Configuration	First Status Undata to KNIV	
Addressing of Indoor Units	First status opdate to KNX	AJAr *
License	Enable object "Error Code [2byte]"	Disabled 🗸
	Enable object "Error Text [14byte]"	Enabled
	(2 ASCII-char Error Code)	

Figure 4.1 Default parameter configuration

With this configuration it's possible to send On/Off (*Control_ On/Off*), change the AC Mode (*Control_ Mode*), the Fan Speed (*Control_ Fan Speed*) and also the Setpoint Temperature (*Control_ Setpoint Temperature*). The Status_ objects, for the mentioned Control_ objects, are also available to use if needed. Also objects *Status_ AC Return Temp* and *Status_ Error/Alarm* are shown.

1.1.1 MD-AC-KNX
1: AC01 Control_ On/Off [DPT_1.001] - 0-Off;1-On
3: AC01 Control_ Mode [DPT_20.105] - 0-Aut;1-Hea;3-Coo;9-Fan;14-Dry
11: AC01 Control_ Fan Speed [DPT_5.001] - Thresholds: 75% || 50% and 83%
17: AC01 Control_ Vanes U-D Swing [DPT_1.002] - 0-Stop;1-Swing
18: AC01 Control_ Setpoint Temperature [DPT_9.001] - °C
22: AC01 Status_ On/Off [DPT_1.001] - 0-Off;1-On
24: AC01 Status_ Mode [DPT_20.105] - 0-Aut;1-Hea;3-Coo;9-Fan;14-Dry
32: AC01 Status_ Fan Speed [DPT_5.001] - 50% and 100% || 33%, 66% and 100%
38: AC01 Status_ Vanes U-D Swing [DPT_1.002] - 0-Stop;1-Swing
40: AC01 Status_ AC Setpoint Temperature [DPT_9.001] - °C
41: AC01 Status_ AC Ambient Reference Temperature [DPT_9.001] - °C
42: AC01 Status_ Error/Alarm [DPT_1.005] - 0-No alarm;1-Alarm
44: AC01 Status_Error Text [DPT_16.001] - Error Text

Figure 4.2 Default communication objects



4.1 General configuration

Inside this parameter's dialog it is possible to activate or change the parameters shown in the **Figure 4.1**.

4.1.1 Download latest database entry for this product and its User Manual from: The first field shows the URL where to download the database and the user manual for the product.

Download latest database entry for this	http://www.intesis.com
product and its User Manual from:	



4.1.2 Intesis Product

This parameter is used to check, before sending the programing, the maximum number of AC units your device supports.

Intesis Product	MD-AC-KNX-1B

Figure 4.4 Parameter detail

Select the version of the gateway that you have:

- INKNXMID001I000, if you only want to control 1 AC unit.
- INKNXMID016I000, if you only want to control up to 16 AC units.
- INKNXMID064I000, if you only want to control up to 64 AC units.

4.1.3 Number of Indoor Units in ETS

This parameter is used to hide/show communication object according to the number of AC units you need to configure. Value ranges go from 1 to 64.

Number of Indoor Units in ETS	1	

Figure 4.5 Parameter detail

In case you introduce a number higher than the maximum number of units allowed by your license, you will get a warning message. This is just for information and will not block the configuration process. Configurations with more indoor units configured than the ones allowed by the license will not be downloaded correctly.

Intesis Product	MD-AC-KNX-1B	•
Number of Indoor Units in ETS	10	
>> WARNING	Too many Indoor Units for this product!	

Figure 4.6 Parameter detail



4.1.4 First Status Updated to KNX

This parameter defines how fast the status is updated to KNX. Depending on the value selected, more or less priority will be assigned to this action. As there are so many parameters available, it is important to consider carefully how to set this parameter.

- If set to "ASAP", all status communication objects will send its value (if needed).
- If set to **"Slow"**, all status communication objects will send its value (if needed), but slower than in the previous option (ASAP).
- If set to **"Super Slow"**, all status communication objects will send its value (if needed), but slower than in the previous option (Slow).

First Status Update to KNX	ASAP

Figure 4.7 Parameter detail

4.1.5 Enable object "Error Code [2byte]"

This parameter shows/hides the *Status_ Error Code* communication object which shows the indoor unit errors, if occurred, in numeric format.

Enable object "Error Code [2byte]"	Disabled 🔹	
------------------------------------	------------	--

₽	43: AC01 Status_	Error Code	[2-by	te signed	d value]	- Error	Code
----------	------------------	------------	-------	-----------	----------	---------	------

Figure 4.8 Communication object	and parameter detail
---------------------------------	----------------------

- If set to **"Disabled"** the object will not be shown.
- If set to **"Enabled"** the *Status_ Error Code [2byte signed value]* object will appear.
 - This object can be read and also sends the indoor unit error, if occurred, in numeric format. If a **"0**" value is shown that means no error.

4.1.6 Enable object "Error Text Code [14byte]"

This parameter shows/hides the *Status_ Error Text Code* communication object which shows the indoor unit errors, if occurred, in text format.

Enable object "Error Text [14byte]"	Enabled 🔹		
(2 ASCII-char Error Code)			

■之 63: AC01 Status_ Error Text [DPT_16.001] - Error Text

Figure 4.9 Communication object and parameter detail

- If set to "Disabled" the object will not be shown.
- If set to "Enabled" the Status_ Error Text Code object will appear.



• This object can be read and also sends the indoor unit error, if occurred, in text format. The errors shown have the same format as in the remote controller and in the error list from the indoor unit manufacturer. If the object's value is empty that means there is no error.

4.2 AC supported features

De	vice: 1.1.1 MD-AC-KNX			
	General configuration	C	All Indees Units support some exercting modes	
	AC supported features	Supported operating modes	An induor onits support same operating modes	_
	Global Mode configuration	> Supported operating modes	Heat - Cool - Fan	•
	Global Fan Speed configuration			
	Global Vanes U-D configuration	Supported fan speeds	All Indoor Units support same fan speeds	-
	Global Temperature configuration			5
	Remote Lock Configuration	> Supported fan speeds	S1 - S2	•
	Addressing of Indoor Units			
	License			

Figure 4.10 Parameter detail

4.2.1 Supported operating modes

This parameter determines all indoor units supported operating modes.

Supported operating modes	All Indoor Units support same operating modes	
> Supported operating modes	Heat - Cool - Fan 🔹	

Figure 4.11 Parameter detail

- If set to **"All Indoor Units support same operating modes"** the supported operating modes will be applied to all indoor units.
- If set to **"Supported modes in each Indoor Unit might differ"**, you will need to select the supported operating modes for each indoor unit individually.

Supported operating modes	Supported modes in each Indoor Unit might diffe 🔻
> Supported modes in AC01	Heat - Cool - Fan
> Supported modes in AC02	Auto - Heat - Cool - Fan 🔹
> Supported modes in AC03	Auto - Heat - Cool - Fan - Dry 🔹
> Supported modes in AC04	Heat - Cool - Fan

Figure 4.12 Parameter detail

4.2.2 Supported fan speeds

This parameter determines all indoor units supported fan speeds.

Supported fan speeds	All Indoor Units support same fan speeds	•
> Supported fan speeds	S1 - S2	•

Figure 4.13 Parameter detail

- If set to **"All Indoor Units support same fan speeds"** the supported operating modes will be applied to all indoor units.
- If set to **"Supported fan speeds in each Indoor Unit might differ"**, you will need to select the supported fan speed for each indoor unit individually.

Supported fan speeds	Supported fan speeds in each Indoor Unit might < 🔻
> Supported fan speeds in AC01	S1 - S2 •
> Supported fan speeds in AC02	Auto - S1 - S2 🔹
> Supported fan speeds in AC03	S1 - S2 - S3 •
> Supported fan speeds in AC04	Auto - S1 - S2 - S3 🔹

Figure 4.14 Parameter detail

4.3 Global mode configuration

)e	evice: 1.1.1 MD-AC-KNX				
	General configuration AC supported features	Enable use of "Operating Mode" objects (for control and status)	Disabled -		
	Global Mode configuration Global Fan Speed configuration	Enable use of "Mode Cool/Heat" objects (for control and status)	Disabled		
	Global Vanes U-D configuration Global Temperature configuration	Enable use of +/- object for Mode	Disabled		
	Addressing of Indoor Units	Enable use of bit-type Mode objects (for control)	Disabled 🔹		
	License	Enable use of bit-type Mode objects (for status)	Disabled •		
		Enable use of Text object for Mode	Disabled		

Figure 4.15 Default Mode Configuration dialog

All the parameters in this section are related with the different mode properties and communication objects.

2: Control_Mode [DPT_20.105 - 1byte] - 0-Aut;1-Hea;3-Coo;9-Fan;14-Dry

■24: Status_ Mode [DPT_20.105 - 1byte] - 0-Aut;1-Hea;3-Coo;9-Fan;14-Dry

The byte-type communication object for Mode works with the DTP_20.105. Auto mode will be enabled with a "**0**" value, Heat mode with a "**1**" value, Cool mode with a "**3**" value, Fan mode with a "**9**" value and Dry mode with a "**14**" value.

4.3.1 Enable use of "Operating Mode" objects

This parameter shows/hides the *Control_* and *Status_ Mode Operating Mode* communication objects.

- 2: Control_Operating Mode [DPT_20.102 1byte] 0-Aut;1-Com;2-Stan;3-Eco;4-Pro
- 23: Status_ Operating Mode [DPT_20.102 1byte] 0-Aut;1-Com;2-Stan;3-Eco;4-

4.3.2 Enable use of Mode Heat / Cool bit obj

This parameter shows/hides the *Control_* and *Status_ Mode Cool/Heat* communication objects.

- 4: Control_ Mode Cool/Heat [DPT_1.100 1bit] 0-Cool;1-Heat
- ■
 Z5: Status_ Mode Cool/Heat [DPT_1.100 1bit] 0-Cool;1-Heat
- $\circ~$ If set to "Disabled" the objects will not be shown.
- If set to **"Enabled"** the *Control_* and *Status_ Mode Cool/Heat* objects will appear.
 - When a "1" value is sent to the *Control_* communication object, **Heat mode** will be enabled in the indoor unit, and the *Status_* object will return this value.
 - When a "O" value is sent to the *Control_* communication object, **Cool mode** will be enabled in the indoor unit, and the *Status_* object will return this value.

4.3.3 Enable use of + / - object for Mode

This parameter shows/hides the *Control_ Mode* +/- communication object which lets change the indoor unit mode by using two different datapoint types.

■ 10: Control_Mode +/- [DPT_1.008 - 1bit] - 0-Up;1-Down

- If set to **"Disabled"** the object will not be shown.
- If set to **"Enabled"** the *Control_ Mode* +/- object and a new parameter will appear.

Enable use of +/- object for Mode	yes 🔹
> DPT type for +/- Mode Object	0-Up / 1-Down [DPT_1.008]

Figure 4.16 Parameter detail

DPT type for +/- Mode Object

This parameter lets choose between the datapoints **0-Up / 1-Down [DPT_1.008]** and **0-Decrease / 1-Increase [DPT_1.007]** for the *Control_ Mode* +/- object.

The sequence followed when using this object is shown below:

Up / IncreaseDown / Decrease

Keep in mind that depending on the indoor unit you have and the available features, Auto mode and Dry mode may not be present.

4.3.4 Enable use of bit-type Mode objects (for control)

This parameter shows/hides the bit-type *Control_ Mode* objects.

- ■↓ 5: Control_ Mode Auto [DPT_1.002 1bit] 1-Set AUTO operating mode
- ■2 6: Control_ Mode Heat [DPT_1.002 1bit] 1-Set HEAT operating mode
- 7: Control_ Mode Cool [DPT_1.002 1bit] 1-Set COOL operating mode
- 8: Control_ Mode Fan [DPT_1.002 1bit] 1-Set FAN operating mode
- 2 9: Control_ Mode Dry [DPT_1.002 1bit] 1-Set DRY operating mode
- If set to **"no"** the objects will not be shown.
- If set to "yes" the Control_ Mode objects for Auto, Heat, Cool, Fan and Dry will appear.
 To activate a mode by using these objects a "1" value has to be sent.

4.3.5 Enable use of bit-type Mode objects (for status)

This parameter shows/hides the bit-type *Status_ Mode* objects.

- 26: Status_ Mode Auto [DPT_1.002 1bit] 1-AUTO is active
- ■27: Status_ Mode Heat [DPT_1.002 1bit] 1-HEAT is active
- 28: Status_ Mode Cool [DPT_1.002 1bit] 1-COOL is active
- 29: Status_ Mode Fan [DPT_1.002 1bit] 1-FAN is active
- 30: Status_ Mode Dry [DPT_1.002 1bit] 1-DRY is active
- If set to **"no"** the objects will not be shown.
- If set to "yes" the Status_ Mode objects for Auto, Heat, Cool, Fan and Dry will appear.
 When enabled, a mode will return a "1" through its bit-type object.
- 4.3.6 Enable use of Text object for Mode

This parameter shows/hides the *Status_ Mode Text* communication object.

31: Status_ Mode Text [DPT_16.001 - 14byte] - ASCII String

Intesis[™] KNX - Midea A.C. (VRF line)

- \circ $\;$ If set to ``no" the object will not be shown.
- If set to "yes" the Status_ Mode Text object will appear. Also, in the parameters, will be shown five text fields, one for each mode, that will let modify the text string displayed by the Status_ Mode Text when changing mode.

> String when mode is AUTO (if available)	AUTO
> String when mode is HEAT	HEAT
> String when mode is COOL	COOL
> String when mode is FAN	FAN
> String when mode is DRY (if available)	DRY

Figure 4.17 Parameter detail

4.4 Fan Speed Configuration dialog

De	vice: 1.1.1 MD-AC-KNX		
	General configuration AC supported features	DPT object type for fan speed	Scaling [DPT_5.001]
	Global Mode configuration	Enable use of "Fan Speed Man/Auto"	Disabled 🗸
	Global Fan Speed configuration	objects	
	Global Vanes U-D configuration	(for control and status)	
	Global Temperature configuration	Enable use of +/- object for Fan Speed	Disabled 🔹
	Remote Lock Configuration	chable ase of 1, object for rail opera	
	Addressing of Indoor Units	Enable use of bit-type Fan Speed objects	Disabled 🔹
	License	(for control)	
		Enable use of bit-type Fan Speed objects (for status)	Disabled
		Enable use of Text object for Fan Speed	Disabled •

Figure 4.18 Default Fan Speed Configuration dialog

All the parameters in this section are related with the Fan Speed properties and communication objects.

4.4.1 DPT object type for fan speed

With this parameter is possible to change de DPT for the *Control_ Fan Speed* and *Status_ Fan Speed* byte-type communication objects. Datapoints Scaling (DPT_5.001) and Enumerated (DPT_5.010) can be selected.

NOTE: Remember that Fan Speeds are selected in the AC supported features tab (see section 4.2.2).

 When "Enumerated [DPT 5.010]" is selected, Control_ Fan Speed and Status_ Fan Speed communication objects for this DPT will appear. Also, depending on the number of fan speeds selected, these objects will be different.

11: Control_ Fan Speed [DPT_5.010] - Speed values: 1,2 || 1,2,3

In the second secon

If this DPT is selected with 2 fan speeds:

The first fan speed will be selected if a **"1"** is sent to the *Control*_ object. The second fan speed will be selected sending a **"2"**.

The *Status*_ object will always return the value for the fan speed selected.

If this DPT is selected with 3 fan speeds:

The first fan speed will be selected if a "**1**" is sent to the *Control*_ object. The second one will be selected sending a "**2**", and the last one sending a "**3**".

The *Status*_ object will always return the value for the fan speed selected.

- ▲ Important: In both cases if a "O" value is sent to the Control_ object, the minimum fan speed will be selected. If a value bigger than "2" (in case of 2 speeds) or bigger than "3" (in case of 3 fan speeds) is sent to the Control_ object, then the maximum fan speed will be selected.
- When **"Scaling [DPT 5.001]"** is selected, *Control_ Fan Speed* and *Status_ Fan Speed* communication objects for this DPT will appear. Also, depending on the number of fan speeds selected, these objects will be different.

If this DPT is selected with 2 fan speeds:

- 11: Control_ Fan Speed [DPT_5.001] Thresholds: 75% || 50% and 83%
- 32: Status_ Fan Speed [DPT_5.001] 50% and 100% || 33%, 66% and 100%

When a value between **0%** and **74%** is sent to the *Control*_ object the first fan speed will be selected.

When a value between **75%** and **100%** is sent to the *Control*_ object, the second speed will be selected.

The *Status* object will return a **50%** for the first fan speed, and a **100%** for the second one.

If this DPT is selected with 3 fan speeds:

12: Control_Fan Speed / 3 Speeds [DPT_5.001 - 1byte] - Thresholds: 50% and 83%

■2 52: Status_ Fan Speed / 3 Speeds [DPT_5.001 - 1byte] - 33%, 66% and 100%

When a value between **0%** and **49%** is sent to the *Control*_ object the first fan speed will be selected.

When a value between **50%** and **83%** is sent to the *Control*_ object, the second speed will be selected.

When a value between **84%** and **100%** is sent to the *Control*_ object, the third speed will be selected.

The *Status*_ object will return a **33%** when the first speed is selected, a **67%** for the second one and a **100%** for the third one.

4.4.2 Enable use of +/- object for Fan Speed

This parameter shows/hides the *Control_ Fan Speed* +/- communication object which lets you increase/decrease the indoor unit fan speed by using two different datapoint types.

■ 16: Control_ Fan Speed +/- [DPT_1.008 - 1bit] - 0-Up;1-Down

- If set to **"no"** the object will not be shown.
- If set to "**yes**" the *Control_ Fan Speed* +/- object and a new parameter will appear.

Enable use of +/- object for Fan Speed	Enabled 🔹
> Fan speed +/- operation	0-Decrease / 1-Increase [DPT_1.007]
> Sequence for +/- object	Auto > S1 > S2 > > SN 🔹

Figure 4.19 Parameter detail

Fan speed +/- operation

This parameter lets choose between the datapoints **0-Up / 1-Down [DPT_1.008]** and **0-Decrease / 1-Increase [DPT_1.007]** for the *Control_ Fan Speed* +/- object.

Sequence for +/- object

This parameter lets choose between the different modes available:

Enable use of +/- object for Fan Speed	Enabled 🔹
> Fan speed +/- operation	0-Decrease / 1-Increase [DPT_1.007]
> Sequence for +/- object	Auto > S1 > S2 > > SN 🔹
Enable use of bit-type Fan Speed objects	S1 > S2 > > SN S1 > S2 > > SN > S1 >
	Auto > S1 > S2 > > SN Auto > S1 > S2 > > SN > Auto > S1 >

• S1>S2>....>SN

Select this option if you don't have Auto mode and you don't want roll-over to be enabled.

• S1>S2>....>SN>S1>...

Select this option if you don't have Auto mode and you want roll-over to be enabled.

• Auto>S1>S2>....>SN

Select this option if you have Auto mode and you don't want roll-over to be enabled.

• Auto>S1>S2>....>SN>Auto>S1>...

Select this option if you have Auto mode and you want roll-over to be enabled.

4.4.3 Enable use of bit-type Fan Speed objects (for Control)

This parameter shows/hides the bit-type Control_ Fan Speed objects.

- 13: Control_Fan Speed 1 [DPT_1.002 1bit] 1-Set Fan Speed 1
- 14: Control_ Fan Speed 2 [DPT_1.002 1bit] 1-Set Fan Speed 2
- 15: Control_Fan Speed 3 [DPT_1.002 1bit] 1-Set Fan Speed 3
- \circ If set to ``no" the objects will not be shown.
- If set to "yes" the Control_ Fan Speed objects for Speed 1, Speed 2 and Speed 3 (if available) will appear. To activate a Fan Speed by using these objects a "1" value has to be sent.
- 4.4.4 Enable use of bit-type Fan Speed objects (for Status)

This parameter shows/hides the bit-type *Status_ Fan Speed* objects.

- 34: Status_ Fan Speed 1 [DPT_1.002 1bit] 1-Fan in speed 1
- 35: Status_ Fan Speed 2 [DPT_1.002 1bit] 1-Fan in speed 2
- 36: Status_ Fan Speed 3 [DPT_1.002 1bit] 1-Fan in speed 3
- If set to **"no"** the objects will not be shown.
- If set to "yes" the Status_ Fan Speed objects for Speed 1, Speed 2 and Speed 3 (if available) will appear. When a Fan Speed is enabled, a "1" value is returned through its bit-type object.

4.4.5 Enable use of Text object for Fan Speed

This parameter shows/hides the *Status_ Fan Speed Text* communication object.

37: Status_ Fan Speed Text [DPT_16.001 - 14byte] - ascii string

- If set to **"no"** the object will not be shown.
- If set to "yes" the Status_ Fan Speed Text object will appear. Also, in the parameters, will be shown two (or three, depending on the number of fan speeds selected) text fields, one for each Fan Speed, that will let modify the text string displayed by the Status_ Fan Speed Text when changing a fan speed.

 String when fan speed is AUTO (if available) 	AUTO
> String when fan speed is 1	SPEED 1
> String when fan speed is 2	SPEED 2
 > String when fan speed is 3 (if available) 	SPEED 3

Figure 4.20 Parameter detail

4.5 Global Vanes U-D configuration

Dev	rice: 1.1.1 MD-AC-KNX		
	General configuration	Fachlaura of Taut abiant fac Varian II D	Dirabled
	AC supported features	Enable use of Text object for valles 0-D	
	Global Mode configuration		
	Global Fan Speed configuration		
	Global Vanes U-D configuration		
	Global Temperature configuration		
	Remote Lock Configuration		
	Addressing of Indoor Units		
	License		

All the parameters in this section are related with the Vane Up-Down properties and communication objects.

4.5.1 Enable use of Text object for Vanes U-D

This parameter lets you choose if you want to use a Text object to determine the U-D vanes position.

Enable use of Text object for Vanes U-D	Disabled					

Figure 4.22 Parameter detail

 $\circ~$ If set to <code>"Disabled"</code> the only communication objects for the Up-Down Vanes shown will be

17: Control_ Vanes U-D Swing [DPT_1.002 - 1bit] - 0-Off;1-Swing

38: Status_ Vanes U-D Swing [DPT_1.002] - 0-Stop;1-Swing

• If set to **"Enabled"** the parameters and communication objects (if enabled in the parameters dialog) for the Up-Down Vanes will be shown.

➡ 39: Status_ Vanes U-D Text [DPT_16.001] - Vanes Text

▲ **Important:** Read the documentation of your indoor unit to check if Up-Down Vanes are available.

4.6 Global temperature configuration

0

De	vice: 1.1.1 MD-AC-KNX		
	General configuration	Fachle use of a (abiant fac Saturiat	Disabled
	AC supported features	Enable use of +/- object for Setpoint	
	Global Mode configuration	Ambient temp, ref, is provided from KNX	Disabled 🗸
	Global Fan Speed configuration	(carefully read User Guide if enabled)	
	Global Vanes U-D configuration		
	Global Temperature configuration		
	Remote Lock Configuration		
	Addressing of Indoor Units		
	License		

Figure 4.20 Default Temperature Configuration dialog

All the parameters in this section are related with the Temperature properties and communication objects.

4.6.1 Enable use of +/- obj for Setpoint

This parameter shows/hides the *Control_ Setpoint Temp* +/- communication object which lets you change the indoor unit setpoint temperature by using two different datapoint types.

19: Control_ Setpoint Temp +/- [DPT_1.008 - 1bit] - 0-Up;1-Down

- If set to **"no"** the object will not be shown.
- If set to "**yes**" the *Control_ Setpoint Temp* +/- object and a new parameter will appear.

Enable use of +/- obj for Setp Temp	yes 🔻
> DPT type for +/- Setp Temp object	0-Up / 1-Down [DPT_1.008]

Figure 4.23 Parameter detail

> DPT type for +/- Setp Temp object

This parameter lets choose between the datapoints **0-Up / 1-Down [DPT_1.008]** and **0-Decrease / 1-Increase [DPT_1.007]** for the *Control_ Setpoint Temp +/-*object.

(Lower limit) 16°C	-	17ºC ≓		\rightarrow	31ºC	32°C (Upper	r limit)
		Up,	/ Incre	ase			
		Dov	vn / De	ecrease			

4.6.2 Ambient Ref. Temp. is provided from KNX

This parameter shows/hides the *Control_ Ambient Temperature* communication object which lets you use an ambient temperature reference provided by a KNX device.

In the second secon

- If set to **"no"** the object will not be shown.
- If set to **"yes"** the *Control_ Ambient Temperature* object will appear. Meant to be enabled when you want the temperature provided by a KNX sensor to be the reference ambient temperature for the air conditioner. Then, the following formula applies for the calculation of real *Control_ Setpoint Temperature* sent of the AC unit:

"AC Setp. Temp" = "Ambient ref. Temp" - ("KNX Amb. Temp." - "KNX Setp Temp.")

- AC Setp. Temp: AC indoor unit setpoint temperature
- Ambient Ref. Temp: AC indoor unit return temperature
- KNX Amb. Temp.: Ambient temperature provided from KNX
- KNX Setp. Temp: Setpoint temperature provided from KNX

As an example, consider the following situation:

User wants: **19°C** ("KNX Setp. Temp.") User sensor (a KNX sensor) reads: **21°C** ("KNX Amb Temp.") Ambient temp. read by Midea system is: **24°C** ("Ambient Ref. Temp")

In this example, the final setpoint temperature that INKNXMID---I000 will send out to the indoor unit (shown in "Setp. Temp.") will become $24^{\circ}C - (21^{\circ}C - 19^{\circ}C) = 22^{\circ}C$. This is the setpoint that will actually be requested to Midea unit.

This formula will be applied as soon as the *Control_ Setpoint Temperature* and *Control_ Ambient Temperature* objects are written at least once from the KNX installation. After that, they are kept always consistent.

Note that this formula will always drive the AC indoor unit demand in the *right* direction, regardless of the operation mode (Heat, Cool or Auto).

4.7 Remote Lock Configuration

Device: 1.1.1 MD-AC-KNX				
General configuration	Frankla was of Domasta Lank akianta	Disabled		
AC supported features	Enable use of Remote Eock objects	UISADIEU *		
Global Mode configuration	Initial state of remote lock	Apply same initial state to all Indoor Units		
Global Fan Speed configuration				
Global Vanes U-D configuration	> Initial state of Remote Lock	Do not initialize 🔹		
Global Temperature configuration				
Remote Lock Configuration				
Addressing of Indoor Units				
License				

Figure 4.24 Parameter detail

All the parameters in this section are related to each AC unit and its Remote-Control commands.

4.7.1 Enable Remote Lock Objects

This parameter is used to show or hide the remote lock objects related to each indoor unit.

21 AC01 Control_ Remote Lock On/Off [DPT_1.003] - 0-Disable;1-Enable
 45 AC01 Status_ Remote Lock On/Off [DPT_1.003] - 0-Disable;1-Enable

4.7.2 Initial state of remote lock

This parameter determines the remote lock status when initializing the gateway.

ce: 1.1.1 MD-AC-KNX				
General configuration		[Taskind		
AC supported features	Enable use of Remote Lock objects	Enabled		
Global Mode configuration	Initial state of remote lock	Apply same initial state to all Indoor Units		
Global Fan Speed configuration				
Global Vanes U-D configuration	> Initial state of Remote Lock	Do not initialize 🔹		
Global Temperature configuration		Do not initialize		
Remote Lock Configuration		Start unlocked		
Addressing of Indoor Units		Start locked		
License				
	e: 1.1.1 MD-AC-KNX General configuration AC supported features Global Mode configuration Global Fan Speed configuration Global Vanes U-D configuration Global Temperature configuration Remote Lock Configuration Addressing of Indoor Units License	te: 1.1.1 MD-AC-KNX General configuration AC supported features Global Mode configuration Global Fan Speed configuration Global Vanes U-D configuration Global Temperature configuration Remote Lock Configuration Addressing of Indoor Units License		

Figure 4.23 Parameter detail

• If set to **"Apply same initial state to all Indoor Units"**, the same initial status will be applied to all indoor units.

• If set to **"Initial state for each Indoor Unit might differ"**, different initial status my be defined for each indoor unit individualy.

In both cases, there 3 different initial statuses:

- Do not initialize: The INKNXMID---I000 will not modify the current status after a gateway re-start.
- Start Unlocked: The INKNXMID---I000 will set the remote lock to "unlocked" after a gateway re-start.
- Start Locked: The INKNXMID---I000 will the remote lock to "locked" after a gateway re-start.

4.8 Addressing of Indoor Units

Device: 1.1.1 MD-AC-KNX							
General configuration AC supported features	Address of AC01	0					
Global Mode configuration Global Fan Speed configuration	Address of AC02	1					
Global Vanes U-D configuration Global Temperature configuration	Address of AC03	2					
Remote Lock Configuration Addressing of Indoor Units	Address of AC04	3					
License	Address of AC05	4					
	Address of AC06	5					
	Address of AC07	6					
	Address of AC08	7					
	Address of AC09	8					
	Address of AC10	9					

Figure 4.24 Parameter detail

In this section you will be able to modify the AC addressing for each AC unit present in the configuration.

4.9 License

Device: 1.1.1 MD-AC-KNX								
General configuration	Articution Code							
AC supported features	Activation Code							
Global Mode configuration								
Global Fan Speed configuration								
Global Vanes U-D configuration								
Global Temperature configuration								
Remote Lock Configuration								
Addressing of Indoor Units								
License								

Figure 4.24 Parameter detail

Use this section to introduce the migration code in case you need to update your box from another version different from the factory default one.

5 Specifications

Envelope	Plastic, type ABS (UL 94 V-0). 2,5 mm thickness				
Dimensions	71 x 71 x 27 mm				
Weight	42g				
Color	White, RAL 9010				
Power supply	29V DC, 7mA				
Power supply	Supplied through KNX bus.				
LED indicators	1 x KNX programming/bus.				
Push buttons	1 x KNX programming.				
Configuration	Configuration with ETS.				
Operating Temperature	From 0°C to 60°C				
Storage Temperature	From -40°C to 85°C				
Isolation Voltage	4000V				
RoHS conformity	Compliant with RoHS directive (2002/95/CE).				
Certifications	CE conformity to EMC directive (2004/108/EC) and Low-voltage directive (2006/95/EC) EN 61000-6-2 EN 61000-6-3 EN 60950-1 EN 50491-3				

6 AC Unit Types compatibility.

A list of Midea indoor unit model references compatible with INKNXMID---I000 and their available features can be found in:

https://www.intesis.com/docs/compatibilities/inxxxmid0xxi000_compatibility

7 Error Codes

Error Code KNX Object	Error in Remote Controller	Error Name	
1	E0	Phase error or error in the phase sequence	
2	E1	Communication error	
3	E2	T1 sensor error	
4	E3	T2A sensor error	
5	E4	T2B sensor error	
6	E5	T3 temperature and T4 temperature Compressor discharge temperature sensors error	
7	E6	Zero cross error detection	
8	E7	EEPROM memory error	
9	E8	Indoor fan speed out of control	
10	E9	Communication error between the main panel and the visualization panel	
11	EA	Compressor's current overload error (4 times)	
12	EB	Inverter module protection	
13	EC	Cooling error	
14	ED	Outdoor unit fault protection	
15	EE	Water level fault detection	
16	EF	Other errors	
101	PO	Vaporizer temperature protection	
102	P1	Thawing or cold air protection	
103	P2	Condenser high temperatures protection	
104	P3	Compressor temperature protection	
105	P4	Evacuation duct temperature protection	
106	P5	Discharge high pressure protection	
107	P6	Discharge low pressure protection	
108	P7	Current overload or under load protection	
109	P8	Compressor's current overload protection	
110	P9	Reserved	
111	PA	Reserved	
112	PB	Reserved	
113	PC	Reserved	
114	PD	Reserved	
115	PE	Reserved	
116	PF	Other protection measures	
-1	-	Communication error between INKNXMIDI000 and Indoor Unit	
-100	-	Licence error / Indoor units not supported by current license	
-200	-	Overconsumption error in EXY bus	

In case you detect an error code not listed, contact your nearest Midea technical support service for more information on the error meaning.

Appendix A – Communication Objects Table

SECTION	OBJECT	NAME		DATAPOINT TYPE			FLA	GS		FUNCTION
SECTION	NUMBER	NAME		DPT_NAME	DPT_ID	R	W	Т	U	FUNCTION
On/Off	1	Control_ On/Off	1 bit	DPT_Switch	1.001		W	т		0 - Off; 1-On
	2	Control_ Operating Mode	1 byte	DPT_HVACMode	20.102		W	т		0 - Auto; 1 - Com; 2 - Stan; 3 - Eco; 4 – Pro
	3	Control_ Mode	1 byte	DPT_HVACControl	20.105		W	т		0 - Auto; 1 - Heat; 3 - Cool; 9 - Fan; 14 - Dry
	4	Control_ Mode Cool/Heat	1 bit	DPT_Cool/Heat	1.100		W	т		0 - Cool; 1 – Heat
	5	Control_ Mode Auto	1 byte	DPT_Scaling	5.001		W	т		1 - Auto
Mada	6	Control_ Mode Heat	1 byte	DPT_Scaling	5.001		W	Т		1 - Heat
Mode	7	Control_ Mode Cool	1 bit	DPT_Bool	1.002		W	Т		1 - Cool
	8	Control_ Mode Fan	1 bit	DPT_Bool	1.002		W	Т		1 – Dry
	9	Control_ Mode Dry	1 bit	DPT_Bool	1.002		W	Т		1 – Fan
	10	Control_ Mode +/-	1 bit	DPT_Step	1.007		W			0 - Decrease; 1 - Increase
	10	Control_ Mode +/-	1 bit	DPT_UpDown	1.008		W			0 - Up; 1 - Down
		Control_ Fan Speed / 2 Speeds	1 byte	DPT_Scaling	5.001		W	Т		0%-74% - Speed 1; 75%-100% - Speed 2
	11	Control_ Fan Speed / 3 Speeds	1 byte	DPT_Scaling	5.001		w	т		0%-49% - Speed 1; 50%-83% - Speed 2; 84%-100% Speed 3
		Control_ Fan Speed / 2 Speeds	1 byte	DPT_Enumerated	5.010		W	т		1 - Speed 1; 2 - Speed 2
Fan Speed		Control_ Fan Speed / 3 Speeds	1 byte	DPT_Enumerated	5.010		w	т		1 - Speed 1; 2 - Speed 2; 3 Speed 3
	12	Control_ Fan Speed Man/Auto	1 bit	DPT_Bool	1.002		w	т		0 – Manual; 1 – Auto
	13	Control_ Fan Speed 1	1 bit	DPT_Bool	1.002		W	т		1 - Fan Speed 1

Intesis[™] KNX - Midea A.C. (VRF line)

	14	Control_ Fan Speed 2	1 bit	DPT_Bool	1.002	W	т	1 - Fan Speed 2
	15	Control_ Fan Speed 3	1 bit	DPT_Bool	1.002	W	Т	1 - Fan Speed 3
	16	Control_ Fan Speed +/-	1 bit	DPT_Step	1.007	W	т	0 - Decrease; 1 - Increase
		Control_ Fan Speed +/-	1 bit	DPT_UpDown	1.008	W	т	0 - Up; 1 - Down
Vanes	17	Control_ Vanes U-D Swing	1 bit	DPT_Bool	1.002	W	т	0 - Off; 1 - Swing
	18	Control_ Setpoint Temperature	2 byte	DPT_Value_Temp	9.001	W	т	17°C to 30°C
Temperature	19	Control_ Setpoint Temp +/-	1 bit	DPT_Step	1.007	W		0 - Decrease; 1 - Increase
		Control_ Setpoint Temp +/-	1 bit	DPT_UpDown	1.008	W		0 - Up; 1 - Down
	20	Control_ Ambient Temperature	2 byte	DPT_Value_Temp	9.001	W	Т	°C value in EIS5 format
Locking	21	Control_ Control Remote Lock	1 bit	DPT_Bool	1.003	W	т	0 - Unlocked; 1 - Locked

On/Off	22	Status_ On/Off	1 bit	DPT_Switch	1.001	R	Т	0 - Off; 1-On
Mode	23	Status_ Operating Mode	1 byte	DPT_HVACMode	20.102	R	Т	0 - Auto; 1 - Com; 2 - Stan; 3 - Eco; 4 - Pro
	24	Status_ Mode	1 byte	DPT_HVACContrMode	20.105	R	Т	0 - Auto; 1 - Heat; 3 - Cool; 9 - Fan; 14 - Dry
	25	Status_ Mode Cool/Heat	1 bit	DPT_Heat/Cool	1.100	R	Т	0 - Cool; 1 - Heat
	26	Status_ Mode Auto	1 bit	DPT_Bool	1.002	R	Т	1 - Auto
	27	Status_ Mode Heat	1 bit	DPT_Bool	1.002	R	Т	1 - Heat
	28	Status_ Mode Cool	1 bit	DPT_Bool	1.002	R	Т	1 - Cool
	29	Status_ Mode Fan	1 bit	DPT_Bool	1.002	R	Т	1 - Fan
	30	Status_ Mode Dry	1 bit	DPT_Bool	1.002	R	Т	1 - Dry
	31	Status_ Mode Text	14 byte	DPT_String_8859_1	16.001	R	т	ASCII String

Intesis[™] KNX - Midea A.C. (VRF line)

User's manual r1 eng

		Status_ Fan Speed / 2 Speeds	1 byte	DPT_Scaling	5.001	R		т	50% - Speed 1; 100% - Speed 2
Fan Speed	32	Status_ Fan Speed / 3 Speeds	1 byte	DPT_Scaling	5.001	R		т	33% - Speed 1; 67% - Speed 2; 100% - Speed 3
		Status_ Fan Speed / 2 Speeds	1 byte	DPT_Enumerated	5.010	R		Т	1 - Speed 1; 2 - Speed 2
		Status_ Fan Speed / 3 Speeds	1 byte	DPT_Enumerated	5.010	R		Т	1 - Speed 1; 2 - Speed 2; 3 - Speed 3
	33	Status_ Fan Speed Man/Auto	1 bit	DPT_Bool	1.002	R		Т	0 – Manual; 1 – Auto
	34	Status_ Fan Speed 1	1 bit	DPT_Bool	1.002	R		Т	1 - Speed 1
	35	Status_ Fan Speed 2	1 bit	DPT_Bool	1.002	R		Т	1 - Speed 2
	36	Status_ Fan Speed 3	1 bit	DPT_Bool	1.002	R		Т	1 - Speed 3
	37	Status_ Fan Speed Text	14 byte	DPT_String_8859_1	16.001	R		Т	ASCII String
Manag	38	Status_ Vane U-D Swing	1 bit	DPT_Bool	1.002	R		Т	0 - Stop; 1 - Swing
vanes	39	Status_ Vane U-D Text	1 bit	DPT_Bool	1.002	R		Т	ASCII String
	40	Status_ AC Setpoint Temp	2 byte	DPT_Value_Temp	9.001	R		Т	16ºC to 32ºC
Error	41	Status_ AC Ambient Ref Temp	2 byte	DPT_Value_Temp	9.001	R		Т	°C value in EIS5 format
	42	Status_ Error/Alarm	1 bit	DTP_Alarm	1.005	R		Т	0 - No Alarm; 1 - Alarm
	43	Status_ Error Code	2 byte	Enumerated		R		Т	0 - No Error; Any other see user's manual
	44	Status_ Error Text code	14 byte	DPT_String_8859_1	16.001	R		Т	2 char MD Error; Empty - none
Remote Lock	45	Status_ Remote Lock	1 bit	DPT_Bool	1.003		W	Т	0 - Unlocked; 1 - Locked

