

Description

The Modbus RTU and Modbus ASCII drivers allow the FieldServer to transfer data to and from devices using Modbus RTU or Modbus ASCII protocol respectively. Data can be transferred over either RS 232 or RS-485. The driver was developed for Modbus Application Protocol Specification V1.1a" from Modbus-IDA. The specification can be found at www.modbus.org.

The FieldServer can emulate either a Server or Client.

There are various register mapping models being followed by various vendors.

To cover all these models FieldServer uses the following three Models.

- **Modicon_5digit** – Use this format where addresses are defined in 0xxxx, 1xxxx, 3xxxx or 4xxxx format. A maximum of 9999 registers can be mapped of each type. This is FieldServer driver's default format.
- **ADU** – Application Data Unit address. Use this format where addresses of each type are defined in the range 1-65536.
- **PDU** – Protocol Data unit address. Use this format where addresses of each type are defined in the range 0-65535.

The key difference between ADU and PDU is for example if Address_Type is ADU and address is 1, the driver will poll for register 0. If Address_Type is PDU, the driver will poll for address 1.

Note 1: If vendor document shows addresses in extended Modicon (i.e. 6 digit) format like 4xxxx then consider these addresses as xxxxx (just omit the first digit) and use either ADU or PDU.

Note 2: The purpose of providing 3 different ways of addressing the Modbus registers is to allow the user to choose the addressing system most compatible with the address list being used. At the protocol level, the same protocol specification is used for all three with the exception of the limited address range for Modicon_5digit.

Connection Facts

FieldServer Mode	Nodes	Comments
Client	1	Only 1 client node allowed on Multidrop systems
Server	255	Actual electrical loading may reduce number of usable server nodes

Formal Driver Type

Serial, Client or Server

Compatibility

FieldServer Model	Compatible	FieldServer Model	Compatible
ProtoCessor	Yes	QuickServer FS-QS-10xx	Yes
ProtoCarrier	Yes	QuickServer FS-QS-12xx	Yes
ProtoNode	Yes	QuickServer FS-QS-20xx	Yes
ProtoAir	Yes	QuickServer FS-QS-22xx	Yes
		QuickServer FS-QS-3x10-F	Yes

Connection Information

Connection Type: RS-232 or RS-485 (two wire, half-duplex)

Baud Rates: 110 – 115200, standard baud rates only

Data Bits: 7, 8

Parity: Even, Odd, None

Multidrop Capability: Yes

Devices Tested

Device	Tested (Factory, Site)
Modbus RTU Devices	Factory
Modbus ASCII Devices	Factory
Liebert Sitelink	Customer
Square D Activar 58	Customer
Triatek	Customer
WonderWare InTouch	Factory
Fix Intellution	Factory
GE Cimplicity	Customer
Modscan	Factory
GE PLEPM	Factory
ABB Extrel	Customer
Controls	Customer
Eurotherm Chessel	Customer
MSA Sentry	Factory
Magnatek	Customer
Many more.....	

Communication Functions

Data Types Supported	
Data Type	Comments
ASCII	8-bit character
Digital	Digital
Float	32-bit IEEE floating point
Long	Unsigned 32-bit integer
Signed	Signed 16-bit integer
Slong	Signed 32-bit integer
Unsigned	Unsigned 16-bit integer
Input_Reg_64bit	Long input data type
64Bit_Reg	Long data type
Input_Double	Double-precision 64-bit IEEE 754 floating point input data type
Double_Reg	Double-precision 64-bit IEEE 754 floating point data type

Function Codes Supported	
Function Codes	Description
01	Read Discrete Output Status (0xxxx)
02	Read Discrete Input Status (1xxxx)
03	Read Output Registers (4xxxx)
04	Read Input Registers (3xxxx)
05	Force Single Coil (0xxxx)
06	Preset Single Register (4xxxx)
15	Force Multiple Coils (0xxxx)
16	Preset Multiple Registers (4xxxx)
17	Report Slave ID